



HANDBUILT IN GERMANY

WWW.OKKO-FX.COM

OKKOFX@GMX.DE

DOMINATOR DISTORTION

USER MANUAL

GAIN

intensity of distortion, from crunch to all-out-distortion

LEVEL

overall volume.

BASS

The Dominator is capable of a huge bass boost. Start with less bass, increase slowly and explore the limits of your amp/cab.

MIDS

cut/boost mid control with neutral middle setting. This is a very powerful control, the character of the sound can be changed quite drastically.

MID RANGE SWITCH

sets the range of the MID control. The switch has three positions:

left position = MID

boost to balance mid-scooped clean settings on your amp, cut for classic heavy metal tones

middle position = LOW MID

boost to fatten thin-sounding pickups, cut a little for better chord clarity, cut more for aggressive modern rhythm sounds

right position = HI MID

boost for pronounced attack and "british" feel, cut for smoother tones

TREBLE

cut/boost control, affects high frequencies only – no interaction with the other controls.

POWER SUPPLY

The Diablo can be run on a 9v battery or a power supply.

The power supply must be a regulated **9VDC** adapter with the 2.1 mm „barrel plug” and negative center pin (standard for the very most pedals of Boss, Ibanez, Fulltone and many other pedals).



The Dominator features an internal circuit that electronically doubles the supplied voltage (18 volts from a 9 volts battery or power supply).

DO NOT SUPPLY MORE THAN 9 VOLTS OR WRONG POLARITY, you may damage the pedal.

DO NOT SUPPLY AC, you will definitely damage the pedal.